

Classification with ETIM

ETIM (Electro-Technical Information Model) is an international standard used to classify technical products – especially in the electrical, construction, and HVAC sectors. For suppliers, ETIM helps you provide accurate product descriptions and makes it easier for customers to find the right products.

Supported ETIM versions

- ETIM 4.0
- ETIM 5.0
- ETIM 6.0
- ETIM 7.0
- ETIM 8.0
- ETIM 9.0

Visit www.etim.de/datenmodell for detailed information and a full overview of ETIM versions.

Implementing ETIM in your catalogue (XML format)

Include ETIM classifications within the **ARTICLE_FEATURES** section.

```
<ARTICLE_FEATURES>
  <REFERENCE_FEATURE_SYSTEM_NAME>ETIM-4.0</REFERENCE_FEATURE_SYSTEM_NAME>
  <REFERENCE_FEATURE_GROUP_ID>EC000240</REFERENCE_FEATURE_GROUP_ID>

  <FEATURE>
    <FNAME>EF000010</FNAME>
    <FVALUE>EV002973</FVALUE>
  </FEATURE>

  <FEATURE>
    <FNAME>EF000007</FNAME>
    <FVALUE>EV000270</FVALUE>
  </FEATURE>
</ARTICLE_FEATURES>
```

The table below outlines how ETIM data maps to the relevant XML fields:

XML field	ETIM value
REFERENCE_FEATURE_SYSTEM_NAME	ETIM version
REFERENCE_FEATURE_GROUP_ID	Class code
FNAME	Code
FVALUE	Value code

Notes

- Always use ETIM in upper case and include the version number with a hyphen (e.g. ETIM-4.0, ETIM-5.0, ETIM-6.0).
- You can add further classifications for each item using other systems such as [ECLASS](#) or [UNSPSC](#). Create a separate <REFERENCE_FEATURE_SYSTEM_NAME> block for each classification system.

A detailed [example](#) is available at the end of this article.

Example: For catalogues listed on the Unite platform for the United Kingdom, the LANGUAGE in the HEADER must be set to 'eng'.

```
<LANGUAGE>eng</LANGUAGE>
```

Implementing ETIM in your catalogue (CSV format)

Enter the ETIM version in the 'REFERENCE_FEATURE_SYSTEM_NAME' column and the class code in 'REFERENCE_FEATURE_GROUP_ID'.

V	W
REFERENCE_FEATURE_SYSTEM_NAME	REFERENCE_FEATURE_GROUP_ID
Klassifikationssystem-Name am Beispiel von ECLASS: ECLASS-Version	Klassifikationssystem-Name am Beispiel von ECLASS: ECLASS
ETIM-4.0	EC000240
ETIM-4.0	EC000240
ETIM-4.0	EC000240

ETIM attributes (code and value code) go in the FNAME(1-10) and FVALUE(1-10) columns.

BA	BB	BC	BD	BE
FNAME1	FVALUE1	FUNIT1	FNAME2	FVALUE2
Feature name 1	Feature value 1	Feature unit 1	Feature name 2	Feature value 2
EF000010	EV002973		EF000007	EF000027
EF000010	EV002973		EF000007	230
EF000010	EV002973		EF000007	110

Practical example: coin-operated machine using ETIM-9.0

When you search for 'coin-operated machine' on the [ETIM site](#), you'll find the following mapping for its properties:

Vending machine

Class code: EC000341
Sector: E M
Group code: EG000040 - Small domestic appliances
Releases: ETIM-8.0, ETIM-9.0

Class version: 5
Revision: 2
Status: Published

Def	Code	Description	Type	Unit	Unit (imp.)	Value code - Description
1	EF000010	Model	A			1 EV000852 Consumption dependant 2 EV000851 Time-dependant
2	EF000002	Nominal voltage	N	V		
3	EF000346	Power consumption	N	VA		
4	EF000143	Type of current	A			1 EV000612 Rotating current 2 EV000460 AC
5	EF000347	Control	A			1 EV000101 Electronic 2 EV000853 Microprocessor
6	EF000348	Insert	A			1 EV006125 Coins 2 EV000850 Value coin
7	EF000349	Fake money restitution	L			
8	EF000350	Indication	A			1 EV002764 1 digit LED 2 EV002763 Double LC display 3 EV000854 3 digit display 4 EV000190 Control light
9	EF000040	Height	N	mm	in	
10	EF000008	Width	N	mm	in	
11	EF000049	Depth	N	mm	in	

For the attributes type, rated voltage, and current type, the following allocation to XML fields applies:

XML field	ETIM value
REFERENCE_FEATURE_SYSTEM_NAME	ETIM-9.0
REFERENCE_FEATURE_GROUP_ID	EC000341
FNAME(1)	EF000010
FVALUE(1)	EV000852
FNAME(2)	EF000002
FVALUE(2)	230
FNAME(3)	EF000143
FVALUE(3)	EV000612

Units such as volts, amps, or millimetres are added automatically, so there's no need to specify them separately as FUNIT. Your Unite catalogue in XML format will show the ETIM-9.0 classification and relevant attributes directly in the item data record (e.g. for a coin-operated machine).

Example:

```
<ARTICLE_FEATURES>
  <REFERENCE_FEATURE_SYSTEM_NAME>ETIM-9.0</REFERENCE_FEATURE_SYSTEM_NAME>
  <REFERENCE_FEATURE_GROUP_ID>EC000341</REFERENCE_FEATURE_GROUP_ID>
```

```
<FEATURE>
  <FNAME>EF000010</FNAME>
  <FVALUE>EV000852</FVALUE>
</FEATURE>

<FEATURE>
  <FNAME>EF000002</FNAME>
  <FVALUE>230</FVALUE>
</FEATURE>

<FEATURE>
  <FNAME>EF000143</FNAME>
  <FVALUE>EV000612</FVALUE>
</FEATURE>
</ARTICLE_FEATURES>
```